

It's recommended to use a soft cloth or gloves when handling the fixture.

Wiring Instructions

1. Attach universal crossbar to J-box, aligning holes to desired location in regard to fireplate screws.
2. Connect positive supply wire (typically black or the smooth, unmarked side of the two-conductor cord) to positive fixture lead with appropriately sized twist on connector.
3. Connect negative supply wire (typically white or the ribbed, marked side of the two-conductor cord) to negative fixture lead.
4. Please refer to the grounding instructions to complete all electrical connections.
5. Tuck the connected wires into the J-box. Align screw holes from fire plate to the universal crossbar. Thread the screws through, tightening the fire plate flush to the wall/ceiling.
6. Raise sconce body over fire plate aligning holes at bottom with tapped rods. Secure sconce body in place using provided screws.
7. Thread glass shade on to sconce body.

Grounding Instructions

For positive grounding in a 3-wire electrical system, fasten the fixture ground wire (typically copper or green plastic coated) to the fixture mounting crossbar with the ground screw.

Note: On straps for screw support fixtures, first install the two mounting screws in strap. Any remaining tapped hole may be used for the ground screw.

Light bulb Replacement

1. Turn glass shade counter clockwise to release from sconce body.
2. Gently pull bulb from socket and replace.
3. Rotate glass shade clockwise to secure to sconce body.

