

It's recommended to use a soft cloth or gloves when handling the fixture.

#### Wiring Instructions

1. Attach crossbar to J-box using provided screws.
2. Connect positive supply wire (typically black or the smooth, unmarked side of the two-conductor cord) to positive fixture lead with appropriately sized twist on connector.
3. Connect negative supply wire (typically white or the ribbed, marked side of the two-conductor cord) to negative fixture lead.
4. Please refer to the grounding instructions to complete all electrical connections.
5. Tuck the connected wires into the J-box. Align center hole from fire plate to threaded rod on crossbar. Tighten back plate flush to the wall using threaded cap.
6. Secure shade to fire plate using provided screws.

#### Grounding Instructions

For positive grounding in a 3-wire electrical system, fasten the fixture ground wire (typically copper or green plastic coated) to the fixture mounting crossbar with the ground screw.

Note: On straps for screw support fixtures, first install the two mounting screws in strap. Any remaining tapped hole may be used for the ground screw.

#### Light bulb Replacement

1. Remove screws at sides of shade to release from back plate.
2. Gently twist bulb in and out of socket. Replace shade.

