

It's recommended to use a soft cloth or gloves when handling the fixture.

#### Wiring Instructions

1. Attach universal crossbar to J-box, aligning holes to desired location in regard to fixture ball screws.
2. Connect positive supply wire (typically black or the smooth, unmarked side of the two-conductor cord) to positive fixture lead with appropriately sized twist on connector.
3. Connect negative supply wire (typically white or the ribbed, marked side of the two-conductor cord) to negative fixture lead.
4. Please refer to the grounding instructions to complete all electrical connections.
5. Tuck the connected wires into the J-box. Align screw holes from back plate to the universal crossbar. Thread the ball screws through, tightening back plate flush to the wall/ceiling.

#### Grounding Instructions

For positive grounding in a 3-wire electrical system, fasten the fixture ground wire (typically copper or green plastic coated) to the fixture mounting crossbar with the ground screw.

Note: On straps for screw support fixtures, first install the two mounting screws in strap. Any remaining tapped hole may be used for the ground screw.

#### Light bulb Replacement

1. Make sure the fixture is off.
2. Gently twist bulb in and out of socket while holding fixture body as to not strain fixture.

